



# Hardwire Smoke & Carbon Monoxide Talking Alarm

Carbon monoxide is an invisible, odourless, poisonous gas that can be fatal when inhaled. It is the #1 cause of unintentional poisoning deaths in North America.



## Features:



• **Ionization Technology** – Better at detecting fast flaming fires.



• **120V AC Direct-Wire** – Interconnects with up to 24 units, of which 18 can be initiating.



• **9V Battery Backup (included)** – Continuous protection in case of power failure.



• **Test / Reset Button** – Tests circuitry and resets alarm.



• **Hush® Button** – Quickly silences nuisance alarms.



• **Talking Alarm** – Voice messages with sounding alarm identify different dangers.

• 2-in-1 unit – Advanced sensors for detecting both CO and smoke.

900-0119



## Specifications:

Product dimensions:	6" x 6" x 1.5" deep
Colour / Case Pack:	White / 6 units
Electrical Rating:	120V AC, 60Hz, 60mA, 9V Battery Backup
Wiring:	Quick connect plug with 8" pigtails
Audio Alarm:	85dB
Temperature Range:	40°F (4.4°C) to 100°F (37.8°C)
Humidity Range:	Up to 85% relative humidity
Sensor:	Ionization and Electrochemical
Limited Warranty:	5 Year
Weight:	0.80lb
UPC:	0-47871-00119-4

